



SDEC Engine Water Cooled Diesel Generator 250kVA 6DTAA8.9-G22

Our Product Introduction

Basic Information

- Place of Origin: CHINA
- Brand Name: DELLENT
- Certification: CE/ISO9001
- Model Number: DE-SC261
- Minimum Order Quantity: 1*20GP
- Price: face to face
- Packaging Details: PLASTIC WRAP OR PLYWOOD CASE
- Delivery Time: 30 DAYS FROM DEPOSIT RECEIVED
- Payment Terms: L/C, T/T
- Supply Ability: 500 PCS PER MONTH



Product Specification

- Name: Water Cooled Diesel Generator 250kVA
- Frequency: 50Hz
- Engine Model: 6DTAA8.9-G22
- Engine Brand: SDEC
- No. Of Cylinder: 6 Cylinder In Line
- Rated Speed: 1500rpm
- Voltage: 400V/230V
- Warranty: 12 Months
- Controller: Deepsea/Smartgen/ ComAp
- Prime Power: 190kW/238kVA
- Standby Power: 209kW/261kVA
- Highlight: **SDEC Water Cooled Diesel Generator, Water Cooled Diesel Generator 250kVA, 250kVA Diesel Generator**

for more products please visit us on dellentpower.com

SDEC Engine 250kVA Water Cooled Diesel Generator

.PRODUCT DESCRIPTION

SDEC Engine 250kVA Water Cooled Diesel Generator

Dellent Power supply the standby power 250kVA water cooled diesel generator with SDEC brand diesel engine model 6DTAA8.9-G22. The water cooled diesel generator with rated output 225kVA / 180kW, standby power 250kVA / 200kW.



250kVA Diesel Generator Powered by SDEC Diesel Engine:

Max. Power	kVA	250.0
	kW	200.0
Rate Power	kVA	225.0
	kW	180.0
Frequency	Hz	50
Rate Voltage	V	400/230
Rate Current	A	324.8

SDEC Diesel Engine:

Engine Manufacturer		Shanghai Diesel Engine Co., Ltd.
Engine Brand		SDEC
Engine Model		6DTAA8.9-G22
No. of Cylinder		6 Cylinder in line
Aspiration		Turbocharged and Intercooler
Governor		Electric
Engine Max. Output Power	kW	242
Displacement	L	8.900
Starting Voltage	V	24
Bore	mm	114
Stroke	mm	144
Lubrication Oil Capacity	L	22-25
Compression Ratio		16.5 : 1
Intake Air Flow	M ³ /Min	N.A
Fuel Consumption at 100% Load	L/H	44.1

Specification of Control Panel:

Controller Brand		Deepsea
Breaker Brand		Delixi
Breaker Capacity	A	400

Battery Charger	Smartgen Model BAC06A
Emergency Stop Button	Supply
Automatic Mains Fail (AMF)	Supply
Fuel Level	Supply
Automatic Transfer Switch	ATS as optional part
Mains Monitor	Supply with DELLENT Function
The control panel supply the full protection with alarm and shutdown of the diesel generator include Start-up fault (generator set shutdown), High coolant temperature (alarm and generator set shutdown), Low oil pressure (alarm and generator set shutdown), Low fuel level (alarm), Low cooling fluid level alarm (as optional), Overload (alarm and generator set shutdown), Battery voltage high (alarm).	
Optional controller: Each model of Deepsea, Smartgen, ComAp brand controller.	

. Why Choose Us:

Dedicated

We are DEDICATED to meet Customers' need.

Enthusiasm

We respond to our Customers' ENTHUSIASM

Loyalty

We cherish our Customers' LOYALTY

Luxury

We aim to establish our own LUXURY brand

Efficient

We offer our EFFICIENT service

Newest

We adopt NEWEST technologies for products

Trust

We strive for winning the TRUST from Customers

. QUALIFICATION CERTIFICATE:



. FACTORY INTERIOR:



- 1: The diesel generator should be placed in a well ventilated area to ensure heat dissipation;
- 2: Diesel generators should regularly inspect and replace vulnerable parts such as engine oil and air filter elements to ensure their normal operation;
- 3: When running diesel generators, attention should be paid to the quality and storage method of fuel, to avoid using inferior fuel or improper storage that may cause malfunctions;
- 4: When using diesel generators, appropriate loads should be used according to requirements to avoid overload or underload leading to faults;



Fuan Dellent Electric & Machinery Co., Ltd.



+8613706938606



jennifer@dellent.com



dellentpower.com

NO.7,JINYE ROADTIEHU INDUSTRIAL AREA CHENGYANG TOWN, FUAN
CITY,NINGDECITY,FUJIAN.CHINA